

# 003 MIDI Mode

This Read Me documents known issues with workarounds, if any, for 003 MIDI Mode.

---

## Known Issues

### **003 Exits MIDI Mode Unexpectedly (Item #87070)**

When using 003 in Third-Party mode and MIDI mode, 003 exits MIDI mode automatically if you make any changes to 003 audio settings. Be sure to configure your audio settings prior to enabling MIDI mode. Once you have configured 003 audio settings, enable 003 MIDI mode.

### **DAE Error -6097 when using 003 in MIDI Mode with Strike (Item #87287)**

On slower machines, when using 003 in MIDI mode to control Strike, you may encounter a DAE error -6097 if you sent continuous controller messages to Strike while Strike is loading a preset. Wait until Strike has finished loading a preset before controlling Strike with 003.

### **003 Port Unavailable to ReWire Client Applications on Windows (Item #87109)**

ReWire-client applications (such as Reason) on Windows will not recognize 003 as a MIDI device (port) while Pro Tools is running. Consequently, to use a ReWire client's "learn" MIDI controller function, you must quit Pro Tools, launch the ReWire-client application as a stand-alone application, and then "learn" 003 controllers. The next time you launch the ReWire-client application with Pro Tools, you can successfully use 003 MIDI mode to control the "learned" parameters in the ReWire-client application.